

# Power Harmonics Analyser MI 2092

High value for money,  
3-phase power quality  
analyser for complete  
power quality  
assessment



**Power Harmonics Analyser is a complete 3-phase, portable power analyser for use in industry, utilities and for general power quality diagnostics purposes.**

- Three current and three voltage inputs combined with an internal memory module allow recording up to 4 weeks
- 64 parameters can be monitored or recorded simultaneously
- Instrument can be programmed either directly or via PC
- MS Windows compatible PC SW PowerLink serves for downloading, management of recorded data and preparation of test reports
- Wide range of accessories makes the instruments suitable for a variety of different applications

### Target applications

- General power quality assessment in distribution and industrial low and middle voltage electric systems
- Capturing and recording of power supply events (shut-down's, interruptions, sags, dips)
- Power factor correction equipment measurements
- Harmonics measurements and filter selection
- Consumption profile recording

### Main features

- High accuracy measurement and recording of power quality parameters (U, I, f, cos  $\varphi$ , PF, P, Q, S, current and voltage harmonics up to 63<sup>rd</sup> order, etc.)
- 4-quadrant measurements (generator and load with capacitive or inductive character)
- Energy counter
- On-Line scope function
- Instrument can be configured either directly or over PC
- Large, high resolution LCD display with backlit
- Windows compatible PowerLink PC SW supports downloading, programming, communication with the instrument and transfer of recorded data to other MS programmes (Excel, Word, etc.)

### Standards:

Instrument is developed and manufactured in accordance with following standards:

**Safety:** IEC/EN 61010-1

**EMC:** IEC/EN 61326-1

**Measurements:** EN 50160, EN 61000-4-30, Class B

### General technical specifications

#### Display

Graphic Liquid Crystal Display with LED backlight, 160 x 116 dots resolution

#### Non - volatile memory

2048 Kbytes SRAM, battery backed

#### Digital hardware specification

A/D con., 14 bit with 128 samples per channel, per period (43 ÷ 68 Hz)

#### Outputs

Communication type: RS232 serial interface

Baud rate: 2400 ÷ 57600 bps

Connector: 9 pin, D-type.

Communication cable: Standard type

#### Power supply

Operating range:

230 V<sub>AC</sub> +10 % ÷ -20 %, 45 ÷ 65 Hz, 8 VA

Optional:

115 V<sub>AC</sub> +10 % ÷ -20 %, 45 ÷ 65 Hz, 8 VA

DC power supply:

Internal 4 x 1.2 V NiMH batteries

Charger: Internal battery charger

Working temperature range: -20 °C ÷ +60 °C

Max. humidity: 85 % RH (0 ÷ 40 °C)

Pollution degree: 2

Protection classification: II, double insulation

Voltage inputs:

CAT III/600 V; optional CAT IV/600 V

Overvoltage category:

AC power supply, CAT III/300 V

Protection degree: IP 64

Dimensions: 265 x 110 x 185 mm

Weight: 2 kg

#### Recorder

Adjustable integration period: 1 s ÷ 900 s

Selected signals: max. 64

Statistics values:

Each period divided in 200 parts (0.1 ms)

Voltage anomalies:

Based on half period, start, duration and extremes of measured voltage

# Technical specification

## AC Voltages

Three-phase AC voltage input (3 differential inputs, L1 - N, L2 - N, L3 - N)  
Input voltage range:  $10 \div 550 V_{RMS\ L-N}$ ,  $900 V_{RMS\ L-L}$

Optional on request:  $600 V_{RMS\ L-N}$  (overload 10 s)  
 $10 \div 750 V_{RMS\ L-N}$ ,  $1000 V_{RMS\ L-L}$   
 $800 V_{RMS\ L-N}$  (overload 10 s)

Resolution: 0.1 V  
Accuracy:  $\pm 0.5\%$  of reading  $\pm 2$  digits  
Crest factor max.:  $1 \div 1.4 @ 550 V_{RMS\ L-N}$   
Frequency range:  $43 \div 68$  Hz mains voltage

## AC Currents

Three-phase AC input for connection to current transducers with voltage output  
Input current (voltage output):  $0.02 \div 1 V_{RMS}$  (from  $0.02 \times I_n \div I_n$ )  
Resolution: 0.3 mV (0.3 A with 1000 A / 1 V)  
Accuracy: ( $\pm 0.5\%$  of reading  $\pm 6$  dig.) + current transformer accuracy  
Crest factor:  $1 \div 2.5 @ 1 V_{RMS}$   
Maximum permissible overload: 150 %  $I_n$  (sinusoidal current)  
Maximum input voltage:  $1 V_{RMS}$

## Phase angle

Consider phase angle data of used current transformer

## Scope

Display options: Waveform of pairs (L1: U1 and I1, L2: U2 and I2,  
L3: U3 and I3),  $U_{1,2,3}$ , and  $I_{1,2,3}$   
Ranging: Auto / manual

## METER – Power measurement

Phase values for selected measuring:  
Measured: voltage (U), current (I),  $\cos \varphi$   
Calculated: active power (P), apparent power (S), reactive power (Q),  
power factor (PF) with its characteristics (C, L, none), inter phase voltage

3-phase values:  
Calculated: active power (Pt), apparent power (St),  
reactive power (Qt), power factor (PFt), neutral current (In);  
Basic accuracy for P, Q, S,:  $\pm 1\%$  of reading  
Resolution for P, Q, S,: 0.01 of displayed value

## SPECTRUM – Harmonics measurement

The instrument computes harmonics on signals sampled with an A/D converter.  
Recording interval: 160 ms (8 cycles)  
Spectrum calculation range: DC – 63<sup>rd</sup>  
Spectrum display range: DC – 25<sup>th</sup>  
Displayed items for selected harmonic: order, relative and absolute value

## Energy

### Displayed results:

- cumulative values (TOTAL)  
- partial cumulative value (SUBTOTAL)  
- values for last integration period (LAST IP)

**Displayed quantities** Active energy (EP), capacitive energy (EQC), inductive energy (EQI)

Basic accuracy:  $\pm 1\%$  of reading  
Resolution: 0.1 of displayed value

## Ordering information:

Standard set

Part No. MI 2092



- Instrument Power Harmonics Analyser
- Current clamp 1000 A/1 V, 3 pcs
- Test tips, 3 pcs
- Alligator clips, 4 pcs
- Voltage measurement cables, 4 pcs
- Mains cable
- PowerLink PC SW package with RS232 cable
- Rechargeable batteries, 4 pcs
- Soft carrying bag
- Small soft carrying bag for current clamps
- User manual
- Handbook "Modern Power Quality Measurement Techniques" on CD
- Product verification data

Standard set

Part No. MI 2092F



Similar content as MI 2092:  
Current clamp 1000 A/1 V, 3 pcs replaced by  
3-phase flexible current clamps 3000/300/30 A, 1 pcs

## Optional accessories:

Photo	Order No.	Acc. description
	A 1033	Current clamp 1000 A/1 V
	A 1037	Current transformer 5 A/1 V
	A 1039	Clamp adapter (for A 1069 and A 1122)
	A 1069	Mini clamp 100 A/1 V to be used with A1039
	A 1122	Mini clamp 5 A/1 V to be used with A1039
	A 1171	USB/RS232 converter with 1 m fixed cable
	A 1179	3-phase flexible current clamps 2000/200/20 A
	A 1257	3-phase flexible current clamps 3000/300/30 A
	A 1287	1-phase flexible current clamps 3000/300/30 A
	S 2014	Safety fuse adapter
	S 2015	Safety flat clamps



**METREL®**

Measuring and Regulation Equipment Manufacturer

METREL d.d.  
Ljubljanska 77  
SI-1354 Horjul  
Tel: + 386 (0)1 75 58 200  
Fax: + 386 (0)1 75 49 226  
E-mail: metrel@metrel.si  
http://www.metrel.si

Note! Photographs in this catalogue may slightly differ from the instruments at the time of delivery. Subject to technical change without notice.