

ONOVO PAV120Bip - Portable Real Time Simulation Amplifier

PAV120Bip is the portable six-phase real time simulation amplifier. This voltage amplifier is similar to PAV120Bi but it has small size and less weight.



Main Specifications

Voltage	6×0 ~ 120V RMS
Max. Output power	>60VA(120V output)
Input signal	0~5V RMS
Voltage Accuracy	<0.1%(5V-120V)
Voltage Typical Accuracy	< 0.05%
Differential input impedance	20k ohm
Gain	25V/V
Harmonic Distortion Ratio	≤0.1%
Linearity	≤0.1%
Phase accuracy	0.2°
Frequency range	DC-5kHz±1dB
Step response	< 20us
Input/output delay	< 20us
Power supply	single phase 110V or 220V AC
Chassis	3U